

## MODKIT 9

### PHOENIX KITS



Panasonic TX-28XD60(Series),TX-25XD60(Series),  
TX-28XD70(Series),TX-29AD70(Series),TXW-36D3(Series),

Replacement of TDA8350Q/5 (IC451)

- 1, Replace C453 with 10mFd 160V (10mFd 250V supplied)
- 2, Check location of F531 (D-PCB) to see if wire is fitted, if so remove link wire and replace with 10 Ohm resistor.
- 3, F532 TR5 1.6 Amp is included in case it should be required,
- 4, R568 33 Ohm .5 Watt is included should it be required

*Since the end result depends on your own skill and fault finding ability, the supplier will accept no responsibility for loss, damage or injury caused by your use of this kit. This is expressly sold on the above understanding and that the decision to use the kit is the responsibility of the kit user.*

See an up to date listing of all our kits on our Web site :-  
[phoenixkits.co.uk](http://phoenixkits.co.uk)