

CAPACITORS – CONVERSION GUIDE

Pico-Farad (pF)	Nano-Farad (nF)	Micro-Farad (mF, μ F, MFD)	Capacitance Code	Pico-Farad (pF)	Nano-Farad (nF)	Micro-Farad (mF, μ F, MFD)	Capacitance Code
10	0.01	0.00001	100	10000	10	0.01	103
15	0.015	0.000015	150	15000	15	0.015	153
22	0.022	0.000022	220	22000	22	0.022	223
33	0.033	0.000033	330	33000	33	0.033	333
47	0.047	0.000047	470	47000	47	0.047	473
68	0.068	0.000068	680	68000	68	0.068	683
100	0.1	0.0001	101	100000	100	0.1	104
150	0.15	0.00015	151	150000	150	0.15	154
220	0.22	0.00022	221	220000	220	0.22	224
330	0.33	0.00033	331	330000	330	0.33	334
470	0.47	0.00047	471	470000	470	0.47	474
680	0.68	0.00068	681	680000	680	0.68	684
1000	1.0	0.001	102	1000000	1000	1.0	105
1500	1.5	0.0015	152				
2200	2.2	0.0022	222				
3300	3.3	0.0033	332				
4700	4.7	0.0047	472				
6800	6.8	0.0068	682				