

MODKIT 37

PHOENIX KITS



**Matsui TVR180R/T/280
Plus AlbaBTv17/1799Y/14SLTX/2099TX,
Decca/TatungTVC563
and Bush and Orion Derivatives**

“Stuck in Stand-by” Kit

Replace IC1099 with the enclosed EEPROM

To avoid damage to EEPROM, Observe the normal rules with regards to electro
Static charge

On screen adjustments,

- 1 **Do not set the clock and sound to minimum**
- 2 Press the Volume Down key on the set and the Channel button (9) on the remote control simultaneously to bring up on the screen the adjustment mode as shown below:-
- 3 Use the 1-7 keys on the remote control to select the options shown, press key 7 to end the adjustment.

- Adjustment Mode TV
- 1, AGC/BRI/COL/Auto
 - 2, Sub Bright Auto
 - 3, AGC manual
 - 4, Colour manual
 - 5, Contrast manual
 - 6, Bright manual

Since the end result depends on your own skill and fault finding ability, the supplier will accept no responsibility for loss, damage or injury caused by your use of this kit. This is expressly sold on the above understanding and that the decision to use the kit is the responsibility of the kit user.

See an up to date listing of all our kits on our Web site :-
phoenixkits.co.uk